

Summary of Updating the Firmware for the CS7000 M17 PLUS

When the radio is bricked:

1. Erase the entire Program Memory using the STM32CubeProgrammer tool.
2. Load Openrtx CS7000P 20241224.dfu or later firmware using the DfuSe Demo tool
3. Load M17PLUS Bootloader B7.06.dfu or later firmware using the DfuSe Demo tool
4. Turn off and on the radio. When you turn it on, you must press the top button and PTT at the same time. If you did it correctly, you should see on the radio screen a picture of a robot and the LED should be blinking green, orange, red.
5. Load M17PLUS HOST V9.00.05.bin or later firmware using the Factory Tool M17 DMR V1.0 or later version.